



## Main Features

- Intel® Core™ i5/ i3/ Pentium Integrated Graphics
- Support Intel® LGA1156, Core™ i5/ i3/ Pentium®
- 1x 82574 PCI Express Gigabit Ethernet
- 1x 82578DM Gigabit Ethernet
- 6x SATA, 8x USB2.0, 2x COM, 1x Parallel
- Support Non-ECC Dual Channel DIMM-DDR3 1066/1333 MHz up to 8GB
- Intel® AMT 6.0

## Product Overview

PEAK 876VL2 is PICMG 1.3 full-size Single Board Computer (SBC), which supports Intel® Core™ i5/i3/Pentium® processors with Hyper-Threading technology. The Intel® Core™ i5/i3/Pentium® supports dual channel non-ECC DDR3 1066/1333 MHz memory in two DIMM slots and a Core™ i5/i3/Pentium® integrated graphics controller. The Q57 Express Chipset PCH manages SATA HDD ports, parallel port. Furthermore, it supports other versatile I/O ports such as two serial ports, eight USB ports, and two PCI Express Gigabit LAN ports. The PEAK 876VL2, with Intel® Core™ i5/ i3/ Pentium® and PCI Express LAN, offers a great solution for advanced industrial application that requires superb display and processing performance.

## Specifications

### CPU Support

- Intel® LGA1156, Core™ i5/ i3/ Pentium®

### Main Memory

- 2x 240-pin DIMM, for up to 8GB dual channel Non-ECC DDR3 1066/1333 SDRAM

### Chipset

- Intel® Q57 Express Chipset PCH

### BIOS

- AMI BIOS
- Plug & Play support
- Advanced Power Management and Advanced Configuration & Power Interface support

### On-board LAN

- 1x Intel® 82578DM PHY for AMT 6.0
- 1x Intel® 82574L PCI Express Gigabit Ethernet
- Support boot from LAN (PXE)
- 2x RJ45 with LED

### Display

- Intel® Core™ i5/ i3/ Pentium® processors Integrated graphics
- Analog display support up to 2048x1536 @ 75Hz for CRT

### I/O Interfaces

- USB 2.0: 8 ports (2 on board, 4 to backplane), 2 ports through I/O Bracket
- Serial port: 2 port, with 2x5pin headers (COM 1 and COM 2)
- SATA HDD: 6 ports, Support RAID 0/1/5/10 and Intel® Matrix Storage
- Parallel port: 1 x 26-pin connector
- IrDA: 1x 5pin header
- GPIO: Supports 4 sets general purpose I/O each with TTL level (5 V) interface
- On-board buzzer x 1
- Power LED/Power On/Reset/SMBUS: 2x 8pin header
- 1x 4pin fan connector (for CPU); 1x 3pin fan connectors (for System)
- IPMB interface through PICMG 1.3 Golden-finger
- I/O On SBC Bracket
  - 1x VGA DB-15 connector
  - 2x RJ45 Gigabit Ethernet LAN port
  - 2x USB 2.0 Ports

### Watchdog Timer

- 1 minute increments from 1 to 255 minutes
- 1 second increments from 1 to 255 seconds
- On-chip RTC with battery backup
- 1x External Li-Ion battery

